

Remote Control Setting	Buttons	Remarks																												
		Press the "ON/OFF" button, the light goes to constant on/off mode, sensor is disabled. Press any button to quit from this mode and the sensor starts to work. No memory for ON-OFF setting after power off. Sensor mode will auto resume after restart power supply.																												
		Press "Reset" button, all parameters are same as setting of DIP switch or factory settings.																												
		Press "Sensor motion" button, the light quits from the constant on/ off mode, and the sensor starts to work (The latest setting stays in validity)																												
		Press "DIM Test" button, the 1-10 V dimming works to test whether the 1-10Vdc dimming ports are connected properly. After 2s, it returns to the latest setting automatically.																												
		NA																												
		Set occupancy light level in a range of 50%-100%, dim level is 2% each time press Dim+/Dim-																												
		NA																												
		<table border="1" data-bbox="783 931 1430 1111"> <thead> <tr> <th>Scene Options</th> <th>Detection Area</th> <th>Hold time</th> <th>Stand-by period</th> <th>Stand-by dim level</th> <th>Daylight Sensor</th> <th>Induction Model</th> </tr> </thead> <tbody> <tr> <td>QS1</td> <td>100%</td> <td>5 min</td> <td>10 min</td> <td>10%</td> <td>30 Lux</td> <td>HS</td> </tr> <tr> <td>QS2</td> <td>100%</td> <td>10 min</td> <td>30 min</td> <td>10%</td> <td>Disable</td> <td>HS</td> </tr> <tr> <td>QS3</td> <td>100%</td> <td>20 min</td> <td>30 min</td> <td>10%</td> <td>Disable</td> <td>HS</td> </tr> </tbody> </table> <p>Note: Detection area / Hold time / Stand-by period / Stand-by dim level / Daylight sensor can be adjusted by pressing the corresponding button. The latest setting will stay valid.</p>	Scene Options	Detection Area	Hold time	Stand-by period	Stand-by dim level	Daylight Sensor	Induction Model	QS1	100%	5 min	10 min	10%	30 Lux	HS	QS2	100%	10 min	30 min	10%	Disable	HS	QS3	100%	20 min	30 min	10%	Disable	HS
	Scene Options	Detection Area	Hold time	Stand-by period	Stand-by dim level	Daylight Sensor	Induction Model																							
	QS1	100%	5 min	10 min	10%	30 Lux	HS																							
	QS2	100%	10 min	30 min	10%	Disable	HS																							
	QS3	100%	20 min	30 min	10%	Disable	HS																							
		Press the "TEST 2S" button can enter the test mode anytime. At the mode, the sensor parameters as below: Detection Area is 100%, Hold Time is 2s, Stand-by Dim Level is 10%, Stand-by Period is 0s, daylight sensor disable. This function only for testing. Quit the mode by pressing "RESET" or any other function buttons.																												
		Press "HS" button to set the detection area to be high sensitive. Press "LS" button to set the detection area to be low sensitive. The adjustment bases on the "Detection Area" parameter you set.																												
	Daylight Sensor Set up daylight threshold: 5Lux/15Lux/30Lux/50Lux/100Lux/150Lux/ Disable																													
	Stand-by period Set up stand-by time: 0S/10S/1 min/3min/5min/10min/30min/+ ∞																													
	Hold time Set up hold time: 5S/30S/1 min/3min/5min/10min/20min/30min																													
	Stand-by dim level Set up stand-by dim level: 10%/20%/30%/50%																													
	Detection Area Set up detection area: 25%/50%/75%/100%																													
	Remote Distance Toggle bottom can set the remote distance of remote control and sensor.																													